SIEMENS

Data sheet

6ES7134-6HD01-0BA1



SIMATIC ET 200SP, ANALOG INPUT MODULE, AI 4XU/I 2-WIRE STANDARD, PACKING UNIT: 1 PIECE, FITS TO BU-TYPE A0, A1, COLOR CODE CC03, MODULE DIAGNOSIS, 16BIT, \pm 1-0,3%

General information	
Product type designation	Al 4x U/I 2-wire
HW functional status	From FS02
Firmware version	
 FW update possible 	Yes
usable BaseUnits	BU type A0, A1
Color code for module-specific color identification plate	CC03
Product function	
● I&M data	Yes; I&M0 to I&M3
 Isochronous mode 	No
Measuring range scalable	No
Engineering with	
 STEP 7 TIA Portal configurable/integrated from version 	V14 / -
 STEP 7 configurable/integrated from version 	V5.6 and higher
 PCS 7 configurable/integrated from version 	V8.1 SP1
 PROFIBUS from GSD version/GSD revision 	One GSD file each, Revision 3 and 5 and higher
 PROFINET from GSD version/GSD revision 	GSDML V2.3
Operating mode	
 Oversampling 	No
• MSI	No
CiR - Configuration in RUN	
Reparameterization possible in RUN	Yes
Calibration possible in RUN	No
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes
Input current	
Current consumption, max.	37 mA; without sensor supply
Encoder supply	
24 V encoder supply	
• 24 V	Yes
Short-circuit protection	Yes
 Output current, max. 	20 mA; max. 50 mA per channel for a duration < 10 s
Power loss	
Power loss, typ.	0.85 W; Without encoder supply voltage
Address area	
Address space per module	
Address space per module, max.	8 byte; + 1 byte for QI information

Authoritic encoding • Nechanical coding element • Type A • Nechanical coding element • Type A • Service on Beseutinis for commercion • Type A • Service on Beseutinis for commercion • Sum of the Service on Beseutinis for commercion • Sum of the Service on	Hardware configuration	
* Nechanical coding element * Type A * Type of mechanical coding element * Type A * Selection of Basedarih for connection variants * Zavide connection * Autority Injury * Aut		Yes
■ *Pipe of mechanical codingle element * 2-wine connection * Authors (inputs) * Authors of manage inputs #	•	
Selection of BaseUnit for connection variants	· ·	Type A
Namber of analog inputs Namber of analog inputs Permissible input current for current input (destruction limit), riex. So mA S		
Number of analog inputs Number of analog input votage for votage input (destruction limit), permissible input current for current input (destruction of the active channels) • 0 to 10 to +10 V — Input resistance (10 to 5 V) • 10 V to +10 V • Input resistance (10 V to +10 V) • S V to +5 V — Input resistance (40 V to +10 V) • 120 kD		BU type A0, A1
permissible input voltage for voltage input (destruction limit), max. Cycle time (all channels), min. Sum of the basic conversion times and additional processing times (depending on the parameterization of the active channels) Input ranges (rated values), voltages • 0 to + 10 V — Input resistance (0 to 10 V) • 1 V to 5 V — Input resistance (1 V to 5 V) • 10 V to +10 V • 10 V to +10 V — Input resistance (-10 V to +10 V) • 120 kΩ • 10 V to +10 V — Input resistance (-10 V to +10 V) • 5 V to +5 V — Input resistance (5 V to +5 V) — Input resistance (6 V to +5 V) — Input resistance (6 V to +5 V) — Input resistance (6 V to +5 V) • 120 kΩ • 10 to 20 mA • 1 must resistance (10 to 20 mA) • 4 m to 20 mA — Input resistance (0 to 20 mA) • 4 m to 20 mA — Input resistance (4 mA to 20 mA) • 4 mid to 20 mA — Input resistance (4 mA to 20 mA) • 4 mid to 20 mA — Input resistance (4 mA to 20 mA) • 4 mid to 20 mA — Input resistance (4 max to 20 mA) • 4 mid to 20 mA — Input resistance (4 max to 20 mA) • 5 mid the time time time time time time time tim	Analog inputs	
permissible input voltage for voltage input (destruction limit), max. Cycle time (all channels), min. Sum of the basic conversion times and additional processing times (depending on the parameterization of the active channels) Input ranges (rated values), voltages • 0 to + 10 V — Input resistance (0 to 10 V) • 1 V to 5 V — Input resistance (1 V to 5 V) • 10 V to +10 V • 10 V to +10 V — Input resistance (-10 V to +10 V) • 120 kΩ • 10 V to +10 V — Input resistance (-10 V to +10 V) • 5 V to +5 V — Input resistance (5 V to +5 V) — Input resistance (6 V to +5 V) — Input resistance (6 V to +5 V) — Input resistance (6 V to +5 V) • 120 kΩ • 10 to 20 mA • 1 must resistance (10 to 20 mA) • 4 m to 20 mA — Input resistance (0 to 20 mA) • 4 m to 20 mA — Input resistance (4 mA to 20 mA) • 4 mid to 20 mA — Input resistance (4 mA to 20 mA) • 4 mid to 20 mA — Input resistance (4 mA to 20 mA) • 4 mid to 20 mA — Input resistance (4 max to 20 mA) • 4 mid to 20 mA — Input resistance (4 max to 20 mA) • 5 mid the time time time time time time time tim		4; Differential inputs
Deministrible injust current for current injust (destruction limit), max.	permissible input voltage for voltage input (destruction limit),	30 V
Sum of the basic convention times and additional processing times (depending on the parameterization of the active channels)	permissible input current for current input (destruction limit),	50 mA
Input ranges (rated values), voltages		
• 0 to +10 V	Input ranges (rated values), voltages	on the parameterization of the active channels)
- Input resistance (0 to 10 V)		Yes: 15 bit
1 V to 5 V		
- Input resistance (1 V to 5 V) • 10 V to +10 V • 15 V to +5 V • 15 V to +5 V • 10 to 20 mA — Input resistance (-5 V to +5 V) Input ranges (rated values), currents • 10 to 20 mA — Input resistance (0 to 20 mA) • 4 mA to 20 mA • 4 mA to 20 mA • 100 Ω; + approx. 0.7 V diode forward voltage Ves; 15 bit • 100 Ω; + approx. 0.7 V diode forward voltage Ves; 15 bit • 100 Ω; + approx. 0.7 V diode forward voltage Ves; 15 bit • 100 Ω; + approx. 0.7 V diode forward voltage Integration and conversion for the input Measurement principle Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration sine, parameterizable • Interference voltage suppression for interference frequency If In Hz • Conversion time (per channel) Smoothing of measured values • Number of smoothing levis • parameterizable • Rooder Connection of signal encoders • for voltage measurement • For voltage measurement • (For voltage measurement as 4-wire transducer Yes — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 5-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 5-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 5-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 6-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 6-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 6-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 6-wire transducer — Burden of 2-wire transmitter,	·	
10 V to +10 V		
- Input resistance (-10 V to +10 V) • 5 V to +5 V Fers; 16 bit incl. sign - Input ranges (rated values), currents • 0 to 20 mA Input resistance (0 to 20 mA) • 4 mA to 20 mA — Input resistance (4 mA to 20 mA) Cable lengtit • 100 Ω; + approx. 0,7 V diode forward voltage Ves; 15 bit — Input resistance (4 mA to 20 mA) Shielded, max. Analog value generation for the inputs Measurement principle Integration and conversion time/resolution per channel • Resolution with overange (bit including sign), max. • Integration time, parameterizable • Integration time, parameterizable • Conversion time (per channel) • Number of smoothing levels • Or or voltage measurement as 2-wire transducer Frooder Connection of signal encoders • for outern measurement as 4-wire transducer • Series under measurement as 4-wire transducer • Series under transmitter, max. • for current measurement as 4-wire transducer From Frouries (relative to input range), (++) Crosstalk between the inputs, min. 50 dB Repeata accuracy in steady state at 25 °C (relative to input range), (+-) Operational error limit (operational limit at 28 °C) • Voltage, relative to input range, (+-) Operational error limit (operational limit at 28 °C) • Voltage, relative to input range, (+-) O .5 % • Current, relative to input range, (+-) • Series model interference peak value of interference recovered requency • Series model interference peak value of interference recovered requency • Series model interference peak value of interference recovered requency • Series model interference peak value of interference recovered requency • Series model interference peak value of interference recovered requency		
5 V to +5 V — Input resistance (-5 V to +5 V) 120 kΩ Input ranges (rated values), currents • 0 to 20 mA Yes; 15 bit — Input resistance (0 to 20 mA) 100 Ω; + approx. 0.7 V diode forward voltage • 4 mA to 20 mA Yes; 15 bit — Input resistance (4 mA to 20 mA) 100 Ω; + approx. 0.7 V diode forward voltage • shelded, max. 1 000 m; 200 m for voltage measurement • shelded, max. 1 000 m; 200 m for voltage measurement Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable Yes • Interference voltage suppression for interference frequency 11 in ½ • Conversion time (per channel) 180 / 60 / 50 ms Smoothing of measured values • Number of smoothing levels • parameterizable Yes • conversion time (per channel) 180 / 60 / 50 ms Encodor Connection of signal encoders • for outgan measurement as 2-wire transducer Yes • for outgan measurement as 4-wire transducer Yes • for outgan measurement as 4-wire transducer Yes • for outgan transmitter, max. 650 Ω • for outgate measurement as 4-wire transducer Yes • for outgate measurement as 4-wire transducer No Errorsfaceuracies Linearity error (relative to input range), (+/-) 0.005 %/K Crossialk between the inputs, min. 50 dB Repeat accuracy in steady state at 25 °C (relative to input range, (+/-) 0.5 % • Current, relative to input range, (+/-) 0.5 % • Current, relative to input range, (+/-) 0.5 % • Current, relative to input range, (+/-) 0.5 % • Current, relative to input range, (+/-) 0.5 % • Current, relative to input range, (+/-) 0.5 % • Series model interference (peak value of interference		
Input resistance (-5 V to +5 V)		
Input ranges (rated values), currents		,
• 0 to 20 mA — Input resistance (0 to 20 mA) 4 m kt o 20 mA — Input resistance (4 mA to 20 mA) — Input resistance (4 mA to 20 mA) — Input resistance (4 mA to 20 mA) 5 bit 100 Ω; + approx. 0.7 V diode forward voltage Cable length • shielded, max. 1 000 m; 200 m for voltage measurement Analog value generation for the inputs Measurement principle Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Interference voltage suppression for interference frequency f1 in t/z • Conversion time (per channel) • Number of smoothing levels • parameterizable • Number of smoothing levels • parameterizable • For ourgan measurement as 2-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer — Burden of 2-wire transmitter, max. • for or current measurement as 4-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer — Consistal between the input, min. 50 dB — Respeat accuracy in steady state at 25 °C (relative to input range, (+-) • Correst, relative to input range, (+-) • Correst, relative to input range, (+-) • Corrent, relative to input range, (+-) • Current, relative to input range, (+-) • Series mode interference (peak value of interference < 70 dB		
- Input resistance (0 to 20 mA) 4 mA to 20 mA Pes; 15 bit Input resistance (4 mA to 20 mA) Pes; 15 bit Input resistance (4 mA to 20 mA) 100 Ω; + approx. 0.7 V diode forward voltage Cable length • shielded, max. 1 000 m; 200 m for voltage measurement Analog value generation for the inputs Measurement principle Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. Integration time, parameterizable • Interference voltage suppression for interference frequency 11 in Hz • Conversion time (per channel) Smoothing of measured values • Number of smoothing levels • parameterizable Encoder Connection of signal encoders • for voltage measurement as 2-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer — Burden of 2-wire transmitter, max. • for or current measurement as 4-wire transducer Frors/accuracy/in steady state at 25 °C (relative to input range), (+/-) Inegretative to input range, (+/-) O,005 %/K Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range, (+/-) O,07 %/ • Current, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Series mode interference (peak value of interference 70 dB		Yes; 15 bit
- Input resistance (4 mA to 20 mA) Cable length • shielded, max. 1 000 m; 200 m for voltage measurement Analog value generation for the inputs Measurement principle integration going for the inputs Resolution with overrange (bit including sign), max. • Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Interference voltage suppression for interference frequency 1f in Hz • Conversion time (per channel) Smoothing of measured values • Number of smoothing levels • parameterizable Yes Finceder Connection of signal encoders • for ourrent measurement as 2-wire transducer — Burden of 2-wire transmitter, max. • for ourrent measurement as 4-wire transducer — For current measurement as 4-wire transducer No Frors/accuracies Linearity error (relative to input range), (+/-) Consetal to between the inputs, min. 5 of B Repeat accuracy in steady state at 25 °C (relative to input range) • Voltage, relative to input range, (+/-) O.5 % • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Voltage interference (peak value of interference < 70 dB	— Input resistance (0 to 20 mA)	100 Ω; + approx. 0.7 V diode forward voltage
Analog value generation for the inputs Measurement principle integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. 16 bit • Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. 16 bit • Integration time, parameterizable Yes • Interference voltage suppression for interference frequency ft in Hz • Conversion time (per channel) 180 / 60 / 50 ms Smoothing of measured values • Number of smoothing levels 4; None; 4/8/16 times • parameterizable Yes Encoder Connection of signal encoders • for voltage measurement as 2-wire transducer Yes • for current measurement as 2-wire transducer Yes • for current measurement as 4-wire transducer No Errors/accuracies Linearity error (relative to input range), (+/-) 0.005 %//K Crosstalk between the inputs, min. 50 dB Repeat accuracy in steady state at 25 °C (relative to input range) • Voltage, relative to input range, (+/-) 0.5 % • Current, relative to input range, (+/-) 0.5 % Basic error limit (operational limit at 25 °C) • Voltage, relative to input range, (+/-) 0.3 % Interference voltage suppression for f = n x (ft +/-1 %), ft = interference < 70 dB		
• shielded, max. Analog value generation for the inputs Measurement principle integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable Yes • Integration time, parameterizable 16.6 / 50 / 60 Hz • Interference voltage suppression for interference frequency f1 in Hz • Conversion time (per channel) 180 / 60 / 50 ms Smoothing of measured values • Number of smoothing levels 4; None; 4/8/16 times • parameterizable Yes • for voltage measurement Yes • for current measurement as 2-wire transducer Yes • for current measurement as 4-wire transducer No • for current measurement as 4-wire transducer No Errors/accuracies Linearity error (relative to input range), (+/-) 0.01 % Temperature error (relative to input range), (+/-) 0.005 %//K Crosstalk between the inputs, min. 50 dB Repeat accuracy in steady state at 25 °C (relative to input range) () 0.5 % • Current, relative to input range, (+/-) 0.5 % Basic error limit (operational limit at 25 °C) • Voltage, relative to input range, (+/-) 0.3 % • Current, relative to input range, (+/-) 0.3 % • Current, relative to input range, (+/-) 0.3 % • Series mode interference (peak value of interference < 70 dB	— Input resistance (4 mA to 20 mA)	100 Ω; + approx. 0.7 V diode forward voltage
Analog value generation for the inputs Measurement principle integrating (Sigma-Delta) Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. 16 bit • Integration time, parameterizable Yes • Interference voltage suppression for interference frequency f1 in Hz 180 / 60 / 50 ms Smoothing of measured values 180 / 60 / 50 ms • Number of smoothing levels 4; None; 4/8/16 times • parameterizable Yes Encoder 2 Connection of signal encoders Yes • for voltage measurement Yes • for current measurement as 2-wire transducer Yes — Burden of 2-wire transmitter, max. 650 Ω • for ourrent measurement as 4-wire transducer No Errors/accuracies Linearity error (relative to input range), (+/-) 0.01 % Temperature error (relative to input range), (+/-) 0.005 %/K Crosstalk between the inputs, min. 50 dB Repeat accuracy in steady state at 25 °C (relative to input range, (+/-) 0.5 % • Current, relative to input range, (+/-) 0.5 % • Current, relative to input range, (+/-) 0.5 % <td< td=""><td>Cable length</td><td></td></td<>	Cable length	
Measurement principle integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration and conversion time/presolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Interference voltage suppression for interference frequency f1 in Hz • Conversion time (per channel) Smoothing of measured values • Number of smoothing levels • parameterizable Possible parameterizable Floroder Connection of signal encoders • for voltage measurement • for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer No Frors/accuracles Linearity error (relative to input range), (+/-) Crosstalk between the inputs, min. 50 dB Repeat accuracy in steady state at 25 °C (relative to input range) • Voltage, relative to input range, (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) Ocar film in overall temperature range • Voltage, relative to input range, (+/-) Ocar film in overall temperature renge • Voltage, relative to input range, (+/-) Os % Basic error limit (operational limit at 25 °C) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Series mode interference (peak value of interference < 70 dB	• shielded, max.	1 000 m; 200 m for voltage measurement
Resolution with overrange (bit including sign), max. 16 bit	Analog value generation for the inputs	
 Resolution with overrange (bit including sign), max. Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Conversion time (per channel) 180 / 60 / 50 ms Smoothing of measured values Number of smoothing levels parameterizable Yes for voltage measurement of or current measurement as 2-wire transducer for current measurement as 4-wire transducer for current measureme	Measurement principle	integrating (Sigma-Delta)
 Integration time, parameterizable Interference voltage suppression for interference frequency f1 in Hz Conversion time (per channel) 180 / 60 / 50 ms Smoothing of measured values Number of smoothing levels parameterizable For voltage measurement for voltage measurement for current measurement as 2-wire transducer For current measurement as 4-wire transducer For vortent measurement as 4-wire transducer For vorrent measurement as 4-wire transducer No Errors/accuracies Linearity error (relative to input range), (+/-) Constalk between the inputs, min. 50 dB Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range Voltage, relative to input range, (+/-) Current, relative to input range, (+/-) So % Current, relative to input range, (+/-) So % Current, relative to input range, (+/-) So % Sourrent, relative to input range, (+/-) Voltage, relative to input range, (+/-) So % Series mode interference (peak value of interference 70 dB 	Integration and conversion time/resolution per channel	
 Interference voltage suppression for interference frequency f1 in Hz Conversion time (per channel) 180 / 60 / 50 ms Smoothing of measured values Number of smoothing levels parameterizable For voltage measurement for voltage measurement as 2-wire transducer Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer So 0 Ω for current measurement as 4-wire transducer No Errors/accuracies Linearity error (relative to input range), (+/-) 0.005 %/K Crosstalk between the inputs, min. 50 dB Repeat accuracy in steady state at 25 °C (relative to input range). oVoltage, relative to input range, (+/-) 0.5 % Current, relative to input range, (+/-) 0.5 % Current, relative to input range, (+/-) 0.5 % Basic error limit (operational limit at 25 °C) Voltage, relative to input range, (+/-) 0.3 % Current, relative to input range, (+/-) 0.3 % Current, relative to input range, (+/-) 0.3 % Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference frequency Series mode interference (peak value of interference 70 dB 	 Resolution with overrange (bit including sign), max. 	16 bit
• Conversion time (per channel) Smoothing of measured values • Number of smoothing levels • parameterizable Pes Encoder Connection of signal encoders • for outlage measurement • for outlage measurement as 2-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer No Errors/accuracies Linearity error (relative to input range), (+/-) Consstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) Ocurrent, relative to i	 Integration time, parameterizable 	Yes
Smoothing of measured values Number of smoothing levels parameterizable Freeder Connection of signal encoders of or voltage measurement for current measurement as 2-wire transducer Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer of or current measurement as 4-wire transducer Inearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range Voltage, relative to input range, (+/-) Current, relative to input range, (+/-) Sesies mode interference (peak value of interference < 70 dB		16.6 / 50 / 60 Hz
 Number of smoothing levels parameterizable Yes Encoder Connection of signal encoders for voltage measurement for current measurement as 2-wire transducer Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer No Errors/accuracies Linearity error (relative to input range), (+/-) 0.01 % Temperature error (relative to input range), (+/-) 0.05 %/K Crosstalk between the inputs, min. 50 dB Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range Voltage, relative to input range, (+/-) 0.5 % Current, relative to input range, (+/-) 0.5 % Basic error limit (operational limit at 25 °C) Voltage, relative to input range, (+/-) 0.3 % Current, relative to input range, (+/-) 0.3 % Current, relative to input range, (+/-) 0.3 % Current, relative to input range, (+/-) 0.3 % Eurrent, relative to input range, (+/-) 0.3 % Current, relative to input range, (+/-) 0.3 % Eurrent, relative to input range, (+/-) 0.3 % First All Manuella Man	Conversion time (per channel)	180 / 60 / 50 ms
Parameterizable Yes Encoder Connection of signal encoders • for voltage measurement Yes • for current measurement as 2-wire transducer Yes — Burden of 2-wire transmitter, max. 650 Ω • for current measurement as 4-wire transducer No Errors/accuracies Linearity error (relative to input range), (+/-) 0.01 % Temperature error (relative to input range), (+/-) 50 dB Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) 0.05 %/// Coperational error limit in overall temperature range • Voltage, relative to input range, (+/-) 0.5 % Basic error limit (operational limit at 25 °C) • Voltage, relative to input range, (+/-) 0.3 % • Current, relative to input range, (+/-) 0.3 % • Current, relative to input range, (+/-) 0.3 % Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference frequency • Series mode interference (peak value of interference < 70 dB	Smoothing of measured values	
Encoder Connection of signal encoders • for voltage measurement Yes • for current measurement as 2-wire transducer Yes — Burden of 2-wire transmitter, max. 650 Ω • for current measurement as 4-wire transducer No Errors/accuracies Linearity error (relative to input range), (+/-) 0.01 % Temperature error (relative to input range), (+/-) 0.005 %//K Crosstalk between the inputs, min. 50 dB Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) 0.05 % range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) 0.5 % Basic error limit (operational limit at 25 °C) • Voltage, relative to input range, (+/-) 0.3 % • Current, relative to input range, (+/-) 0.3 % Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference frequency • Series mode interference (peak value of interference < 70 dB	Number of smoothing levels	4; None; 4/8/16 times
Connection of signal encoders • for voltage measurement • for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. 650 Ω • for current measurement as 4-wire transducer No Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. 50 dB Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) Assice error limit (operational limit at 25 °C) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) 0.3 % • Current, relative to input range, (+/-)	 parameterizable 	Yes
 for voltage measurement for current measurement as 2-wire transducer Burden of 2-wire transmitter, max. for current measurement as 4-wire transducer for current measurement as 4-wire transducer No Errors/accuracies Linearity error (relative to input range), (+/-) 0.01 % Temperature error (relative to input range), (+/-) 0.005 %/K Crosstalk between the inputs, min. 60 dB Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range Voltage, relative to input range, (+/-) Current, relative to input range, (+/-) Sasic error limit (operational limit at 25 °C) Voltage, relative to input range, (+/-) Current, relative to input range, (+/-) Current, relative to input range, (+/-) Series mode interference (peak value of interference 70 dB	Encoder	
• for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. 650 Ω • for current measurement as 4-wire transducer No Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) Basic error limit (operational limit at 25 °C) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) O.3 % • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Series mode interference (peak value of interference < 70 dB	Connection of signal encoders	
- Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer No Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. 50 dB Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) Basic error limit (operational limit at 25 °C) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Series mode interference (peak value of interference < 70 dB	 for voltage measurement 	Yes
• for current measurement as 4-wire transducer No	• for current measurement as 2-wire transducer	Yes
Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. So dB Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range Voltage, relative to input range, (+/-) Current, relative to input range, (+/-) Voltage, relative to input range, (+/-) Voltage, relative to input range, (+/-) Current, relative to input range, (+/-) Voltage, relative to input range, (+/-) Voltage, relative to input range, (+/-) Voltage relative to input range, (+/-) Series mode interference (peak value of interference < 70 dB		650 Ω
Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Series mode interference (peak value of interference < 70 dB		No
Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. So dB Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Series mode interference (peak value of interference < 70 dB	Errors/accuracies	
Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Series mode interference (peak value of interference < 70 dB	Linearity error (relative to input range), (+/-)	0.01 %
Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) • Series mode interference (peak value of interference < 70 dB		0.005 %/K
range), (+/-) Operational error limit in overall temperature range • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) Basic error limit (operational limit at 25 °C) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) • Current, relative to input range, (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference frequency • Series mode interference (peak value of interference < 70 dB	·	
 Voltage, relative to input range, (+/-) Current, relative to input range, (+/-) 0.5 % Basic error limit (operational limit at 25 °C) Voltage, relative to input range, (+/-) Current, relative to input range, (+/-) O.3 % Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference frequency Series mode interference (peak value of interference 70 dB 		0.05 %
 Current, relative to input range, (+/-) Basic error limit (operational limit at 25 °C) Voltage, relative to input range, (+/-) Current, relative to input range, (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference frequency Series mode interference (peak value of interference 70 dB 	Operational error limit in overall temperature range	
Basic error limit (operational limit at 25 °C) • Voltage, relative to input range, (+/-) • Current, relative to input range, (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference frequency • Series mode interference (peak value of interference < 70 dB	 Voltage, relative to input range, (+/-) 	0.5 %
 Voltage, relative to input range, (+/-) Current, relative to input range, (+/-) 0.3 % Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference frequency Series mode interference (peak value of interference 	• Current, relative to input range, (+/-)	0.5 %
 Current, relative to input range, (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference frequency Series mode interference (peak value of interference 70 dB 	Basic error limit (operational limit at 25 °C)	
Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference frequency • Series mode interference (peak value of interference < 70 dB	 Voltage, relative to input range, (+/-) 	0.3 %
Series mode interference (peak value of interference < 70 dB	• Current, relative to input range, (+/-)	0.3 %
	Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = inter	ference frequency
· · · · · · · · · · · · · · · · · · ·	 Series mode interference (peak value of interference < rated value of input range), min. 	70 dB

Common mode voltage, max.	10 V
Common mode interference, min.	90 dB
Interrupts/diagnostics/status information	30 42
Diagnostics function	Yes
Alarms	
Diagnostic alarm	Yes
Limit value alarm	No
Diagnoses	
Monitoring the supply voltage	Yes
Wire-break	Yes; at 4 to 20 mA
• Short-circuit	Yes; with 1 to 5 V or 2-wire mode: Short-circuit of the encoder supply to ground or of an input to the encoder supply
Group error	Yes
Overflow/underflow	Yes
Diagnostics indication LED	
 Monitoring of the supply voltage (PWR-LED) 	Yes; green LED
Channel status display	Yes; green LED
for channel diagnostics	No
for module diagnostics	Yes; green/red LED
Potential separation	
Potential separation channels	
• between the channels	Yes; channel group-specific between 2-wire current input group and voltage input group
 between the channels and backplane bus 	Yes
between the channels and the power supply of the electronics	Yes; only for voltage inputs
Permissible potential difference	
between the inputs (UCM)	10 V DC
Isolation	
Isolation tested with	707 V DC (type test)
Standards, approvals, certificates	
Suitable for applications according to AMS 2750	Yes; Declaration of Conformity, see online support entry 109757262
Suitable for applications according to CQI-9	Yes
Ambient conditions	
Ambient temperature during operation	
 horizontal installation, min. 	-30 °C; < 0 °C as of FS02
 horizontal installation, max. 	60 °C
 vertical installation, min. 	-30 °C; < 0 °C as of FS02
vertical installation, max.	50 °C
Altitude during operation relating to sea level	
Installation altitude above sea level, max.	5 000 m; Restrictions for installation altitudes > 2 000 m, see manual
Dimensions	
Width	15 mm
Height	73 mm
Depth	58 mm
Weights	
Weight, approx.	31 g
	_

last modified:

9/7/2023